

OPERATION INSTRUCTIONS

1. Turn the ON/OFF switch to "OFF" and connect power cord to 115 V electrical outlet.
2. Fill the hopper with quarters. For best results fill hopper about half full and add more quarters as it empties.

FOR \$10 QUARTER ROLLS

1. Set the Bulk/Wrap switch to the "Wrap" position.
2. Slide the bank quarter wrapper onto the wrapping tool and fold the top even with the top surface of the tool.
3. Slide the roll tube down over the wrapper and tool until it stops.
4. Pull the roll tube off and place in the support ring below the coin chute. (Note: the bank wrapper with the bottom end folded should stay inside the roll tube, ready to accept coins.)
5. Press the "*COUNT 40*" button, then turn ON/OFF switch to the "ON" position.
6. Quarters will now feed automatically into the roll tube. When 40 quarters (\$10) have been counted, the motor will stop. (The motor will not start again until the COUNT 40 button is again pressed.)
7. Remove the roll tube from the holder by pushing the quarter roll out the top by inserting finger in the bottom while at the same time folding the top of the quarter roll. This completes the counting, wrapping and sealing of 40 quarters into the \$10 bank wrapper.
8. When the next wrapper has been loaded and you are ready to fill the wrapper, press the "*COUNT 40*" button, and quarters will begin to fall into the roll and again stop when the \$10 count is reached. Note: While quarters are being counted, the next bank wrapper can be loaded onto the wrapper tool in preparation for the next cycle.

FOR BULK COUNT

1. Move the ON/OFF switch to the "OFF" position and set the Bulk/Wrap switch in the "Bulk" position.
2. Press the "ZERO" button on the digital counter to set it to zero.
3. Fill the hopper with quarters.
4. Place the bulk coin tray under the coin chute.
5. Turn the ON/OFF switch to "ON." Quarters will be counted until this switch is turned off. The total count of quarters (number of quarters, not dollars) is shown on the digital counter and will remain until cleared by pressing the "ZERO" button.

WARNING: To prevent injury, remove the power plug from the wall outlet before performing maintenance or attempting to remove quarters which may have jammed. Do not operate the counter without the hinged safety cover in place.

MOON PRODUCTS, LLC

3111 E. Celeste Way
Salt Lake City, UT 84109
(801) 486-1794